


Service Manual



Colour Television

TX-32PK2

EURO-4 Chassis

SPECIFICATIONS

Power Source:	220-240V a.c., 50Hz	High Voltage:	31,5kV $\pm$ 1kV
Power Consumption:	137W	Picture Tube:	W76LPX955X06 76cm
Stand-by Power Consumption:	1,4W	Audio Output: (Music Power)	Front Left/Right 2 x 20W Centre 20W Surround 2 x 15W 8 Ω Impedance
Aerial Impedance:	75 Ω unbalanced, Coaxial Type	Dolby Surround Out (Rear)	5 x Dolby Surround Out RCA
Receiving System:	PAL I, PAL-525/60 M.NTSC NTSC (AV only)	External Speaker connections	2 x Rear 1 x Centre
Receiving Channels:	UHF E21-E69	Headphones:	8 Ω Impedance 3,5mm
Intermediate Frequency:		Accessories supplied :	Remote Control 2 x R6 (UM3) Batteries TS-800DP Video Cabinet / Speaker Pack
Video/Audio		Dimensions:	
Video	39,5MHz	Height:	558mm
Audio	33,5MHz	Width:	812mm
	32,95MHz (NICAM)	Depth:	572mm
Colour	35,07MHz	Net weight:	58,5kg
Terminals:		Specifications are subject to change without notice. Weights and dimensions shown are approximate.	
AV1 IN	Video (21 pin) 1V p-p 75 Ω Audio (21 pin) 500mV rms 10k Ω RGB (21 pin)	NOTE: This Service Manual should be used in conjunction with the EURO-4 Technical guide.	
AV1 OUT	Video (21 pin) 1V p-p 75 Ω Audio (21 pin) 500mV rms 1k Ω		
AV2 IN	Video (21 pin) 1V p-p 75 Ω Audio (21 pin) 500mV rms 10k Ω S-Video IN Y: 1V p-p 75 Ω (21-pin) C: 0,3V p-p 75 Ω		
AV2 OUT	Video (21 pin) 1V p-p 75 Ω Audio (21 pin) 500mV rms 1k Ω Selectable output (21 pin)		
AV3 IN	S-Video IN Y: 1V p-p 75 Ω (4-pin) C: 0,3V p-p 75 Ω Audio (RCAx2) 500mV rms 10k Ω Video (RCAx1) 1V p-p 75 Ω		

Panasonic

Panasonic CS (U.K.) Ltd.
WILLOUGHBY ROAD,
BRACKNELL,
BERKS.,
RG12 8FT.

CONTENTS

SAFETY PRECAUTIONS.....	2
SERVICE HINTS.....	3
SERVICE POSITION.....	4
ADJUSTMENT PROCEDURE AND FACTORY SETTINGS.....	5
WAVEFORM PATTERN TABLE.....	6
ALIGNMENT SETTINGS.....	7
BLOCK DIAGRAMS.....	8
PARTS LOCATION.....	13
REPLACEMENT PARTS LIST.....	14
SCHEMATIC DIAGRAMS.....	27
CONDUCTOR VIEWS.....	32

SAFETY PRECAUTIONS

GENERAL GUIDE LINES

1. It is advisable to insert an isolation transformer in the a.c. supply before servicing a hot chassis.
2. When servicing, observe the original lead dress in the high voltage circuits. If a short circuit is found, replace all parts that have been overheated or damaged by the short circuit.
3. After servicing, see that all the protective devices such as insulation barriers, insulation papers, shields and isolation R-C combinations are correctly installed.
4. When the receiver is not being used for a long period of time, unplug the power cord from the a.c. outlet.
5. Potentials as high as 32,5kV are present when this receiver is in operation. Operation of the receiver without the rear cover involves the danger of a shock hazard from the receiver power supply. Servicing should not be attempted by anyone who is not familiar with the precautions necessary when working on high voltage equipment. Always discharge the anode of the tube.
6. After servicing make the following leakage current checks to prevent the customer from being exposed to shock hazard.


LEAKAGE CURRENT COLD CHECK

1. Unplug the a.c. cord and connect a jumper between the two prongs of the plug.
2. Turn on the receiver's power switch.
3. Measure the resistance value with an ohmmeter, between the jumpered a.c. plug and each exposed metallic cabinet part on the receiver, such as screw heads, aerials, connectors, control shafts etc. When the exposed metallic part has a return path to the chassis, the reading should be between 4M ohm and 20M ohm. When the exposed metal does not have a return path to the chassis, the reading must be infinite.

LEAKAGE CURRENT HOT CHECK

1. Plug the a.c. cord directly into the a.c. outlet. Do not use an isolation transformer for this check.
2. Connect a 2k Ω 10W resistor in series with an exposed metallic part on the receiver and an earth, such as a water pipe.
3. Use an a.c. voltmeter with high impedance to measure the potential across the resistor.

4. Check each exposed metallic part and check the voltage at each point.
5. Reverse the a.c. plug at the outlet and repeat each of the above measurements.
6. The potential at any point should not exceed 1,4Vrms. In case a measurement is outside the limits specified, there is a possibility of a shock hazard, and the receiver should be repaired and rechecked before it is returned to the customer.



X-RADIATION WARNING

1. The potential sources of X-Radiation in TV sets are the high voltage section and the picture tube.
2. When using a picture tube test jig for service, ensure that the jig is capable of handling 32,5kV without causing X-Radiation.

NOTE: It is important to use an accurate periodically calibrated high voltage meter.


1. Set the brightness to minimum.
2. Measure the high voltage. The meter should indicate. 31,5kV $\pm$ 1kV.
If the meter indication is out of tolerance, immediate service and correction is required to prevent the possibility of premature component failure.
3. To prevent any X-Radiation possibility, it is essential to use the specified tube.

SERVICE HINTS

How to remove the rear cover

- 1. Remove the 10 screws as shown in Fig.2.

SCREWS



SCREWS


Fig.2.

LOCATION OF CONTROLS

M-Board

C-Board

K-Board



Y-Board

Z-Board

Focus

Screen

H-Board

E-Board

F.B.T.

P-Board

Fig.3.

HOW TO MOVE THE CHASSIS INTO SERVICE POSITION

1. Remove the bead clamber from the mains lead and affix, using back cover screw, into top right-hand cabinet rib **(A)**, shown in **Fig.4**.
2. Remove 2 screws **(B)**, as shown in **Fig.5**, and remove speaker assembly.
3. Hold and lift the rear of the chassis and gently pull the chassis toward you, as shown in **Fig.4**.
4. Release the respective wiring clips and rotate the chassis vertically through 90°, anti-clockwise.
5. Locate the base of the chassis frame into location **(C)**, shown in **Fig.6 / Fig.8**.
6. Clip the chassis frame onto the bead clamber, shown in **Fig.6 / Fig.7**.
7. After servicing replace the bead clamber and speaker, and ensure all wiring is returned to its original position before returning the receiver to the customer.





Fig.4.



Screws
(B)

Fig.5.



Fig.7.




Fig.6.

(C)




Fig.8.

ADJUSTMENT PROCEDURE

Item / Preparation	Adjustments
+B SET-UP 1. Receive a Greyscale signal. 2. Set the controls :- Brightness Minimum Contrast Minimum Volume Minimum	1. Set the +B voltage up as follows:- Adjust R811 so that B2 shows 148V±1V. 2. Confirm the following voltages. B9 5 ± 0,25V B10 5 ± 0,25V B5 12 ± 0,5V B11 33 ± 1,5V B4 16 ± 1V B7 8 ± 0,5V B12 26 ± 1V B8 5,5 ± 0,5V B3 35 ± 1V B13 15 ± 1V B1 200 ± 10V B14 -15 ± 1V
CUT OFF / Ug2 Test 1. Receive a Greyscale signal. 2. Degauss the tube externally. 3. Set the TV into Service Mode 1. 4. Select Cut off mode.	To adjust Cutoff connect an oscilloscope to the Blue cathode. Press " STR " and adjust "cutoff" value using the " Yellow " and " Blue " buttons until the black level is 160V±5V press " STR " to store the value. Remove the oscilloscope. Select Ug2 adjustment and adjust the screen VR until the display shows "O.K."

FACTORY SETTINGS

To return customer settings to factory settings and clear owner ID of all information input by the customer, enter Self-Check mode. Press the down (**-v**) button on the customer controls at the front of the TV set, at the same time pressing the **STATUS** button  on the remote control. To exit Self Check, switch off the TV set at the power button.

NOTE: Self Check should only be used when refurbishing the TV set and not during normal repair work.

VDP	O.K.	PCB	O.K.
TUN	O.K.	Cab	O.K.
E2	O.K.	Sum	Factory use only
MSP	O.K.		
DPL	O.K.		
OPTION 1	00		
OPTION 2	A1		
OPTION 3	02		
OPTION 4	41		
OPTION 5	B1		
OPTION 6	E9		


















If the CCU ports have been checked and found to be incorrect or not located then " - - " will appear in place of "O.K.".

Service Aids

To aid in the service of our current chassis there are a number of Service Aids which have been made available.

- **LUCI** interface kit (**Linked Utility Computer Interface**)
 Part number: TZS6EZ002
 This contains interface and cables for connecting TV service connector and a PC as well as diagnostic software. As new models are introduced upgrade software will become available.
- **VICI** (**Visual Interactive Computer Information**)
 These C.D.'s contain multimedia documentation providing quick access to service information.
 Part No. TZS7EZ006, TZS7EZ005 & TZS8EZ001
 1. Service Manuals
 2. Instruction Books
 3. Technical Information
- **TASMIN** (**T**echnically **A**dvanced **S**ystem for **M**ultimedia **I**nteractive **N**otes)
 As well as providing a first step towards more interactive training this product also achieves quick access to Technical Information.

WAVEFORM PATTERN TABLE




ALIGNMENT SETTINGS

(The figures below are nominal and used for representative purposes only.)


Alignment Function		Settings / Special features
Horizontal Position	H-Pos 061	Optimum setting.
Vertical Position	V-Pos 005	Optimum setting.
Horizontal Amplitude	H-Amp 055	Optimum setting.
Vert. Amplitude	V-Amp 054	Optimum setting.
EW-amplitude	E/W-Amp1 -128	Optimum setting.
EW-amplitude	E/W-Amp2 006	Optimum setting.
Trapezium-comp	Trapez-1 047	Optimum setting.
Trapezium-comp	Trapez-2 -128	Optimum setting.
Vertical Linearity	V-Lin 006	Optimum setting.
Vertical Symmetry	V-Sym 002	Optimum setting.
DVCO	DVCO -005	Receive a PAL Colour Bar Pattern. For DVCO alignment press " Blue " button, wait until the colours are changing slowly and press " STR ".
Cut-off DC	Cut-off 0171	To adjust Cutoff connect an oscilloscope to the blue cathode. Press " STR " and adjust "cutoff" value using the " Yellow " and " Blue " buttons until the black level is $160V \pm 5V$ press " STR " to store the value. Remove the oscilloscope.
Ug2 Test	Ug2 055 O.K.	Select Ug2 adjustment and adjust the screen VR until the display shows "O.K."
Highlight Lowlight	High 0902 0777 0864 Low 0117 0132 0112	Optimum setting.
Sub-Brightness	Sub-Brightness 255	Optimum setting.




VIDEO BLOCK DIAGRAM




AUDIO BLOCK DIAGRAM




DOLBY BLOCK DIAGRAM



CONTROL BLOCK DIAGRAM




POWER SUPPLY BLOCK DIAGRAM



PARTS LOCATION

NOTE:

The numbers on the exploded view below refer to the mechanical section of the Replacement Parts List.



REPLACEMENT PARTS LIST

Important Safety Notice

Components Identified by  mark have special characteristics important for safety.
* When replacing any of these components, use only manufacturers specified parts.
In case of ordering these spare parts, please always add the complete Model-Type number to your order.

Cct Ref	Parts Number	Description
MECHANICAL PARTS		
1	EAB10106BL	LEFT SPEAKER
2	EAB10106BR	RIGHT SPEAKER
3	EAS8E002-A	REAR SPEAKER COMPLETE
4	EAS8E350-A	CENTRE SPEAKER
5	ENG27506GR	TUNER
6	EUR511210	REMOTE CONTROL
7	HFV598-E06	DAF BLOCK
8	TBMA060	PANASONIC BADGE
9	TBX8E068	POWER BUTTON
10	TKP8E1285	SPEAKER NET
11	TKP8E1302	REAR AV PANEL
12	TKP8E1312	LID DOOR
13	TKU8E00480	BACK COVER
14	TKY8E390	CABINET
15	TLK8E05123	DEGAUSS COIL
16	TMW8E023	CONTROL BRACKET
17	TMX8E037	CHASSIS FRAME
18	TNP8EC003AA	C.P.C.B.
19	TNP8EE009DL	E.P.C.B.
20	TNP8EH002AB	H.P.C.B.
21	TNP8EK005AC	K.P.C.B.
22	TNP8EM021AA	M.P.C.B.
23	TNP8EP016AA	P.P.C.B.
24	TNP8EY017AA	Y.P.C.B.
25	TNP8EZ001AD	Z.P.C.B.
26	TQF8E2843	MODEL LABEL
27	TSX8E0015S	DOLBY SPEAKER WIRE 12M
28	TSX8E0032	POWER CORD
29	UR51EC904A	BATTERY COVER (REMOTE)
30	VP19151	C.R.T. FIXING SCREW
31	W76LPX955X06	C.R.T.
32	ZTBZAD550A	ANODE CABLE
33	ZTFM05007A	F.B.T.
MISCELLANEOUS COMPONENTS		
	31221212478	FIX CLIP
	832AG11D-ESL	IC SOCKET
	F9-4-220	RELAY
	PLCC-84-T	84 PIN IC SOCKET
	TBM8E1935-1	PRESET LABEL
	TBM8E1936-1	BLANKING LABEL
	TBM8E1943	AV LABEL
	TEK6940	LID CATCH
	TES8E019	POWER BUTTON SPRING
	TKJ8E011	SPEAKER GRILLE
	TKP8E1288	LED COVER
	TKP8E1300	I.R. COVER
	TLK8E05124	GEOMAGNETIC COIL
	TMW8E030	LED HOLDER
	TMX8E022	DOLBY BRACKET
	TPC8E4750	OUTER CARTON
	TPC8E4793	OUTER CARTON

Cct Ref	Parts Number	Description
	TPD8E689	TOP CUSHION
	TPD8E690	BOTTOM CUSHION
	TPD8E703	SUB CUSHION
	TPD8E706	SPEAKER CUSHION-SET
	TS-800DP	TV STAND
	UM-3DJ-2P	BATTERY PACK
CK420	VP19001	C.R.T. BUSH
CK421	VP19001	C.R.T. BUSH
CK422	VP19001	C.R.T. BUSH
CK423	VP19001	C.R.T. BUSH
R802	232266296706	THERMISTOR
RL580	DH12D1-O-Q	RELAY
RL801	TSE1885-1	RELAY
S351	0330770044	CRT SOCKET
INSTRUCTION BOOKS		
	TQB8E2777	ENGLISH
I.C.s		
IC251	LA4282	AUDIO OUTPUT
IC351	TDA6103Q-N3	R.G.B. OUTPUT
IC451	LA7845N	VERTICAL OUTPUT
IC601	VDP3120BPCC2	VIDEO PROCESSOR
IC701	TEA2031A	E/W CORRECTION
IC801	STRF6654LF51	POWER SUPPLY
IC850	SE140N	ERROR AMPLIFIER
IC851	L78M12MRB	12V REGULATOR
IC853	AN78L08TA	8V REGULATOR
IC1061	RPM-637CBRL	LED RECEIVER
IC1101	SDA5450C59	MICRO PROCESSOR
IC1102	27C2001-L08	EPROM *
IC1103	XDG2-01JA	EAROM *
IC1104	MN1381-R(TA)	RESET
IC1105	MN1381-T(TA)	RESET
IC1900	LA6515	EARTH CORRECTION
IC2101	MSP3410DPOB4	AUDIO PROCESSOR
IC2201	AN6554NSF-E2	OPERATIONAL AMPLIFIER
IC2221	AN6554NSF-E2	OPERATIONAL AMPLIFIER
IC2401	DPL3519APOA1	DOLBY PROCESSOR
IC2402	AN6554	OPERATIONAL AMPLIFIER
IC2403	AN78L08TA	8V REGULATOR
IC2404	NJM4556AD	HEADPHONE AMPLIFIER
IC2701	STR10006-S	POWER SUPPLY
IC2703	TDA2030AV	AUDIO AMPLIFIER
IC2704	TDA2030AV	AUDIO AMPLIFIER
IC3401	TEA2114	VIDEO SWITCHING
IC3901	AN5422K	DYNAMIC FOCUS
IC3902	L78M12MRB	12V REGULATOR
FUSES		
F802	19181-3.15	FUSE
F8021	EYF52BC	FUSE HOLDER
F8022	EYF52BC	FUSE HOLDER
R2711	TSF19632	FS LINK

Cct Ref	Parts Number	Description
DIODES		
D251	MA2180BLFS	DIODE
D253	MA700TA5	DIODE
D254	MA700TA5	DIODE
D354	1SR124-4AT82	DIODE
D355	1SR124-4AT82	DIODE
D356	1SR124-4AT82	DIODE
D357	MA165TA5	DIODE
D358	MA165TA5	DIODE
D359	MA165TA5	DIODE
D360	MTZJT-7715A	DIODE
D361	MA165TA5	DIODE
D362	MA165TA5	DIODE
D363	MA165TA5	DIODE
D364	MA165TA5	DIODE
D453	MA165TA5	DIODE
D454	ERA15-02V3	DIODE
D456	MTZJT-775.6C	DIODE
D457	MA165TA5	DIODE
D501	MA165TA5	DIODE
D502	1SR124-4AT82	DIODE
D511	MA4047	DIODE
D552	RU3LFA1	DIODE
D553	1SR124-4AT82	DIODE
D554	1SR124-4AT82	DIODE
D556	MA165TA5	DIODE
D557	EU02	DIODE
D558	1SR124-4AT82	DIODE
D580	ERD07-15L7	DIODE
D581	MA165TA5	DIODE
D601	DAN217T146	DIODE
D603	DAN217T146	DIODE
D605	DAN212KT146	DIODE
D606	MA165TA5	DIODE
D607	MA4051	DIODE
D609	1SR124-4AT82	DIODE
D615	STZ6.2NT146	DIODE
D616	STZ6.2NT146	DIODE
D618	MTZJT-778.2C	DIODE
D701	MA165TA5	DIODE
D702	MTZJT-775.1C	DIODE
D704	MA29TA5	DIODE
D705	MTZJT-775.6C	DIODE
D801	RBV-608LF-B	DIODE
D803	1SR124-4AT82	DIODE
D804	1SR124-4AT82	DIODE
D805	TLP621GR-LF2	PHOTO COUPLER
D806	1SR124-4AT82	DIODE
D850	RU4BLF-L1	DIODE
D851	MTZJT776.2B	DIODE
D852	MA165TA5	DIODE
D853	MA2180BLFS	DIODE
D854	TVSRU2AMLFA5	DIODE
D855	FML22SLF610	DIODE
D856	RU4AMLF-M1	DIODE
D857	MTZJT-775.1C	DIODE
D858	MA165TA5	DIODE
D859	MA165TA5	DIODE
D861	MA165TA5	DIODE
D862	MTZJT-7736A	DIODE
D863	MA165TA5	DIODE
D865	MA165TA5	DIODE
D866	MA165TA5	DIODE
D867	EK06-V0	DIODE
D868	1N4150T-77	DIODE
D869	1N4150T-77	DIODE

Cct Ref	Parts Number	Description
D870	MA165TA5	DIODE
D871	1N4150T-77	DIODE
D873	MTZJT-775.6C	DIODE
D874	1SR124-4AT82	DIODE
D875	BZX79A75A26A	DIODE
D901	MA165TA5	DIODE
D902	MA165TA5	DIODE
D904	MA165TA5	DIODE
D905	MA165TA5	DIODE
D906	RLS72TE-11	DIODE
D1061	LN81RPHL	DIODE
D1101	MA165TA5	DIODE
D1102	MA165TA5	DIODE
D1104	MA165TA5	DIODE
D1105	MA165TA5	DIODE
D2101	MA723TA5	DIODE
D2102	MA723TA5	DIODE
D2103	MA723TA5	DIODE
D2104	MA723TA5	DIODE
D2105	MTZJT-778.2C	DIODE
D2303	MA723TA5	DIODE
D2304	MA723TA5	DIODE
D2401	MA165TA5	DIODE
D2402	MA165TA5	DIODE
D2403	MTZJT-7712C	DIODE
D2404	MTZJT-7712C	DIODE
D2405	MTZJT-7712C	DIODE
D2406	MTZJT-7712C	DIODE
D2409	MA165TA5	DIODE
D2705	EG01CV0	DIODE
D2706	1SR124-4AT82	DIODE
D2707	TVSEH1LF-F7	DIODE
D2708	MA4075	DIODE
D2709	1SR124-4AT82	DIODE
D2710	1SR124-4AT82	DIODE
D2711	RU4AMLF-M1	DIODE
D2714	MA165TA5	DIODE
D2715	MA165TA5	DIODE
D2716	MA165TA5	DIODE
D2717	MA165TA5	DIODE
D2718	MTZJT-779.1C	DIODE
D2719	MA165TA5	DIODE
D2720	1SR124-4AT82	DIODE
D3201	MTZJT-778.2C	DIODE
D3202	MTZJT-778.2C	DIODE
D3203	MA165TA5	DIODE
D3901	MTZJT-779.1C	DIODE
D3907	ERA22-06V3	DIODE
D3908	ERA22-06V3	DIODE
D3909	MA165TA5	DIODE
D3910	RP1HLFA5	DIODE
D3911	RP1HLFA5	DIODE
D3912	1SS254T-77	DIODE
D3915	MTZJT-7710D	DIODE
D3917	MA165TA5	DIODE
D3920	MA165TA5	DIODE
D3921	MTZJT-7724D	DIODE
TRANSISTORS		
Q101	BC847B	TRANSISTOR
Q102	BC847B	TRANSISTOR
Q104	BC847B	TRANSISTOR
Q105	BC847B	TRANSISTOR
Q251	2SD1328STX	TRANSISTOR
Q252	2SD1328STX	TRANSISTOR
Q253	BC847B	TRANSISTOR
Q254	BC847B	TRANSISTOR

Cct Ref	Parts Number	Description	Cct Ref	Parts Number	Description
Q301	BC847B	TRANSISTOR	Q2429	BC857B	TRANSISTOR
Q302	FMY4T148	TRANSISTOR	Q2430	BC847B	TRANSISTOR
Q303	BC847B	TRANSISTOR	Q2431	BC847B	TRANSISTOR
Q304	FMY4T148	TRANSISTOR	Q2701	BC557B/126	TRANSISTOR
Q305	BC847B	TRANSISTOR	Q2702	2SA684R	TRANSISTOR
Q306	FMY4T148	TRANSISTOR	Q2704	BC847B	TRANSISTOR
Q351	2SA1767	TRANSISTOR	Q2705	BC847B	TRANSISTOR
Q352	2SA1767	TRANSISTOR	Q2706	BC857B	TRANSISTOR
Q353	2SA1767	TRANSISTOR	Q3001	BC847B	TRANSISTOR
Q354	BC857B	TRANSISTOR	Q3006	BC847B	TRANSISTOR
Q451	BC857B	TRANSISTOR	Q3007	BC847B	TRANSISTOR
Q503	2SD2398-M2	TRANSISTOR	Q3201	BC847B	TRANSISTOR
Q551	2SD1577LB	TRANSISTOR	Q3202	BC847B	TRANSISTOR
Q552	2SC1473-RN	TRANSISTOR	Q3203	BC857B	TRANSISTOR
Q580	BC847B	TRANSISTOR	Q3204	BC857B	TRANSISTOR
Q701	BC857B	TRANSISTOR	Q3205	BC847B	TRANSISTOR
Q850	2SD1273PLB	TRANSISTOR	Q3206	BC847B	TRANSISTOR
Q851	BC857B	TRANSISTOR	Q3207	BC847B	TRANSISTOR
Q852	2SC1383-S	TRANSISTOR	Q3208	BC847B	TRANSISTOR
Q853	BC847B	TRANSISTOR	Q3209	BC847B	TRANSISTOR
Q854	BC847B	TRANSISTOR	Q3401	BC847B	TRANSISTOR
Q855	BC847B	TRANSISTOR	Q3402	BC847B	TRANSISTOR
Q856	BC847B	TRANSISTOR	Q3601	BC847B	TRANSISTOR
Q857	2SA1018QTA	TRANSISTOR	Q3901	BC847B	TRANSISTOR
Q905	BC847B	TRANSISTOR	Q3902	BC847B	TRANSISTOR
Q906	BC847B	TRANSISTOR	Q3903	BC847B	TRANSISTOR
Q907	BC857B	TRANSISTOR	Q3904	BC857B	TRANSISTOR
Q908	2SA1535ARLB	TRANSISTOR	Q3905	2SK1006RF122	TRANSISTOR
Q909	2SC3944ARLB	TRANSISTOR	Q3906	2SC4572RB	TRANSISTOR
Q950	BC847B	TRANSISTOR	Q3907	BC847B	TRANSISTOR
Q951	FMY4T148	TRANSISTOR	Q3908	BC847B	TRANSISTOR
Q1051	BC847B	TRANSISTOR	Q3911	BC847B	TRANSISTOR
Q1062	BC847B	TRANSISTOR	Q3912	BC847B	TRANSISTOR
Q1101	BC847B	TRANSISTOR	Q3917	BC847B	TRANSISTOR
Q1104	BC847B	TRANSISTOR	TRANSFORMERS		
Q1105	BC847B	TRANSISTOR	T501	ETH19Y173AY	TRANSFORMER
Q1106	BC847B	TRANSISTOR	T801	ETS42AE256AD	TRANSFORMER
Q1107	BC847B	TRANSISTOR	T802	ETP35KAN619U	TRANSFORMER
Q1108	BC847B	TRANSISTOR	T2701	ETS35AA3Y7AD	TRANSFORMER
Q2101	BC857B	TRANSISTOR	T3901	ETF18L32B	TRANSFORMER
Q2102	BC857B	TRANSISTOR	COILS		
Q2103	BC857B	TRANSISTOR	L104	EXCELSA35T	COIL
Q2301	BC847B	TRANSISTOR	L106	TLTACT100K	COIL
Q2302	BC857B	TRANSISTOR	L107	TLTACT6R8K	COIL
Q2303	BC847B	TRANSISTOR	L301	TLTACT4R7K	COIL
Q2304	BC857B	TRANSISTOR	L302	TLTACT4R7K	COIL
Q2401	BC857B	TRANSISTOR	L451	EXCELSA35T	COIL
Q2402	BC857B	TRANSISTOR	L501	EXCELSA35T	COIL
Q2403	BC857B	TRANSISTOR	L580	ELC08D682E	COIL
Q2404	BC857B	TRANSISTOR	L581	ELHKL057B	COIL
Q2405	BC847B	TRANSISTOR	L582	ELC18B102E	COIL
Q2406	BC847B	TRANSISTOR	L584	ELH5L6120	COIL
Q2407	BC847B	TRANSISTOR	L585	ELC18B151L	COIL
Q2409	BC857B	TRANSISTOR	L601	TLTACT4R7K	COIL
Q2410	BC857B	TRANSISTOR	L602	TLTACT4R7K	COIL
Q2416	BC857B	TRANSISTOR	L603	TLTACT4R7K	COIL
Q2417	BC847B	TRANSISTOR	L604	TLTACT4R7K	COIL
Q2418	BC847B	TRANSISTOR	L606	TLTACT4R7K	COIL
Q2419	BC847B	TRANSISTOR	L607	ELJFC2R2KF	COIL
Q2420	BC847B	TRANSISTOR	L701	ELC10D682E	COIL
Q2421	BC847B	TRANSISTOR	L850	EXCELSA35T	COIL
Q2423	BC857B	TRANSISTOR	L851	EXCELSA35T	COIL
Q2425	BC857B	TRANSISTOR	L852	ELEIE470KA	COIL
Q2426	BC857B	TRANSISTOR	L855	EXCELSA35T	COIL
Q2427	BC847B	TRANSISTOR	L856	EXCELSA39V	COIL
Q2428	BC857B	TRANSISTOR	L901	EXCELSA24T	COIL

Cct Ref	Parts Number	Description						
L902	EXCELSA24T	COIL						
L1061	TLT331K991R	COIL						
L1103	TLTACT100K	COIL						
L1104	EXCELSA35T	COIL						
L1105	ELJFC2R2KF	COIL						
L2101	TLTACT100K	COIL						
L2103	EXCELSA35T	COIL						
L2104	TLTACT4R7K	COIL						
L2401	TLTACT3R3K	COIL						
L2402	TLTACT3R3K	COIL						
L2403	TLTACT101K	PEAKING COIL						
L2404	ELC08D3R3E	COIL						
L2405	ELC08D3R3E	COIL						
L2703	EXCELSA35T	COIL						
L2704	EXCELSA35T	COIL						
L2705	EXCELSA35T	COIL						
L2706	EXCELSA35T	COIL						
L2707	EXCELSA35T	COIL						
L2708	EXCELSA35T	COIL						
L2709	EXCELSA35T	COIL						
L2710	ELC08D3R3E	COIL						
L2711	ELC08D3R3E	COIL						
L2714	ELC08D3R3E	COIL						
L2715	ELC08D3R3E	COIL						
L3001	ELEMV1R5MA	COIL						
L3002	ELEMV1R5MA	COIL						
L3003	ELEMV1R5MA	COIL						
L3004	ELEMV1R5MA	COIL						
L3005	ELEBR2R2KA	COIL						
L3006	ELEBR2R2KA	COIL						
L3007	TLTACT2R2K	COIL						
L3201	ELEBR6R8KA	COIL						
L3202	ELEBR6R8KA	COIL						
L3203	TLT390K991R	COIL						
L3204	TLT331K991R	COIL						
L3401	ELESN2R2KA	COIL						
L3402	ELESN2R2KA	COIL						
L3902	ELEKN103KA	COIL						
FILTERS								
L804	ELF18N012A	LINE FILTER						
L1901	ELF18N012A	LINE FILTER						
CRYSTALS								
X601	4730007267	CRYSTAL						
X1101	TSSA121	CRYSTAL						
X2101	4730007158	CRYSTAL						
X2401	4730007158	CRYSTAL						
RESISTORS								
	ERC12GK825	SOLID	0.5W	10%	8M2 Ω			
C101	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA1	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA1	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA2	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA2	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA3	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA4	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA5	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA5	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA6	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA7	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA8	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA8	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA9	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA10	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA11	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA12	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA13	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA14	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA15	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA16	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA17	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA18	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA19	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA20	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA20	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA21	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA21	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA22	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA23	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA23	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA24	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA25	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA26	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA27	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA28	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA29	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA30	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA31	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA32	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA33	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA34	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA35	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA36	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA37	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA38	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA39	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA40	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA43	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA44	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA45	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA46	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA47	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA48	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA49	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA50	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA51	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA52	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA53	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA54	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA55	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA56	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA57	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA58	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA59	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JA60	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JA61	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JSE10	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE12	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE18	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE22	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE26	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE33	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE35	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE42	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE48	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSE49	ERJ8GEY0R00	S.M.CARB	.125W	5%	0 Ω			
JSM7	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSM8	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSM10	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSM14	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSP09	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			
JSP15	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω			

Cct Ref	Parts Number	Description			
JSZ004	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
L2201	ERQ14AJW220	METAL	0.25W	5%	22 Ω
R101	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R102	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R103	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R104	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R105	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R106	ERJ6GEYJ681	S.M.CARB	0.1W	5%	680 Ω
R107	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R111	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R112	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R113	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R114	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R115	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R116	ERJ6GEYJ562	S.M.CARB	0.1W	5%	5K6 Ω
R117	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R118	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R121	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R251	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R252	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R253	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R254	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R255	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R256	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R258	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R260	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R261	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R262	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R263	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R264	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R265	ERD25TJ2R2	CARBON	0.25W	5%	2R2 Ω
R266	ERD25TJ2R2	CARBON	0.25W	5%	2R2 Ω
R267	ERF7ZK4R7	WOUND	7W	10%	4R7 Ω
R268	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R269	ERQ14AJ101	METAL	0.25W	5%	100 Ω
R271	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R272	ERF7ZK4R7	WOUND	7W	10%	4R7 Ω
R301	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω
R302	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R303	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R304	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R305	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω
R306	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R307	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R308	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R309	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω
R310	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R311	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R312	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R351	ERJ6GEYJ302	S.M.CARB	0.1W	5%	3K Ω
R352	ERJ6GEYJ302	S.M.CARB	0.1W	5%	3K Ω
R353	ERJ6GEYJ302	S.M.CARB	0.1W	5%	3K Ω
R354	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R355	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R356	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R357	ERDS1TJ114	CARBON	0.5W	5%	110K Ω
R358	ERDS1TJ114	CARBON	0.5W	5%	110K Ω
R359	ERDS1TJ114	CARBON	0.5W	5%	110K Ω
R363	ERD25TJ103	CARBON	0.25W	5%	10K Ω
R364	ERD25TJ103	CARBON	0.25W	5%	10K Ω
R365	ERD25TJ103	CARBON	0.25W	5%	10K Ω
R366	ERDS1TJ152	CARBON	0.5W	5%	1K5 Ω
R367	ERDS1TJ152	CARBON	0.5W	5%	1K5 Ω
R368	ERDS1TJ152	CARBON	0.5W	5%	1K5 Ω
R369	ERD25TJ472	CARBON	0.25W	5%	4K7 Ω
R370	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω

Cct Ref	Parts Number	Description			
R372	ERQ12AJ121	FUSIBLE	0.5W	5%	120 Ω
R373	ERJ6GEYJ220	S.M.CARB	0.1W	5%	22 Ω
R374	ERD25TJ274	CARBON	0.25W	5%	270K Ω
R375	ERJ6GEYJ684	S.M.CARB	0.1W	5%	680K Ω
R376	ERJ6GEYJ183	S.M.CARB	0.1W	5%	18K Ω
R377	ERQ12HKR22	FUSIBLE	0.5W	5%	R22 Ω
R378	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R379	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R380	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R381	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R451	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R452	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R453	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R454	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R455	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R456	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R457	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R458	ERD25TJ1R5	CARBON	0.25W	5%	1R5 Ω
R459	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R460	ERDS1TJ221	CARBON	0.5W	5%	220 Ω
R461	ERW2PK1R2	WOUND	2W	10%	1R2 Ω
R463	ERD25TJ222	CARBON	0.25W	5%	2K2 Ω
R464	ERJ6GEYJ752	S.M.CARB	0.1W	5%	7K5 Ω
R465	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R502	ERJ6GEYJ511	S.M.CARB	0.1W	5%	510 Ω
R506	ERD25TJ560	CARBON	0.25W	5%	56 Ω
R507	ERG2FJ470H	METAL	2W	5%	47 Ω
R509	ERDS1TJ152	CARBON	0.5W	5%	1K5 Ω
R510	ERDS1FJ152	CARBON	0.5W	5%	1K5 Ω
R555	ERQ12HKR33	METAL	0.5W	5%	R33 Ω
R558	ERDS1TJ124	CARBON	0.5W	5%	120K Ω
R559	ERQ12HKR33	METAL	0.5W	5%	R33 Ω
R560	ERJ6GEYJ274	S.M.CARB	0.1W	5%	270K Ω
R561	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R563	ERJ6GEYJ334	S.M.CARB	0.1W	5%	330K Ω
R564	ERJ6GEYJ623	S.M.CARB	0.1W	5%	62K Ω
R566	ERJ6GEYJ563	S.M.CARB	0.1W	5%	56K Ω
R567	ERF72K4R7	WOUND	7W	5%	4R7 Ω
R580	ERG1SJ101	METAL	1W	5%	100 Ω
R581	ERG1SJ152	METAL	1W	5%	1K5 Ω
R583	ERG1SJ152	METAL	1W	5%	1K5 Ω
R584	ERG3FJ222H	METAL	3W	5%	2K2 Ω
R585	ERG3FJ222H	METAL	3W	5%	2K2 Ω
R587	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R588	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R589	ERDS1TJ680	CARBON	0.5W	5%	68 Ω
R590	ERD25TJ101	CARBON	0.25W	5%	100 Ω
R601	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R602	ERJ6GEYJ821	S.M.CARB	0.1W	5%	820 Ω
R603	ERJ8GEYJ103	S.M.CARB	1.25W	5%	10K Ω
R604	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R605	ERD25TJ331	CARBON	0.25W	5%	330 Ω
R606	ERD25TJ331	CARBON	0.25W	5%	330 Ω
R607	ERJ6GEYJ821	S.M.CARB	0.1W	5%	820 Ω
R608	ERJ6GEYJ271	S.M.CARB	0.1W	5%	270 Ω
R609	ERJ6GEYJ122	S.M.CARB	0.1W	5%	1K2 Ω
R610	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R611	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R612	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R613	ERJ6GEYJ152	S.M.CARB	0.1W	5%	1K5 Ω
R615	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R622	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R636	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R645	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R647	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R648	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω

Cct Ref	Parts Number	Description			
R650	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R651	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R652	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R653	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R654	ERJ6GEYJ622	S.M.CARB	0.1W	5%	6K2 Ω
R655	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R658	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R659	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R660	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R701	ERQ12AJ101	FUSIBLE	0.5W	5%	100 Ω
R702	ERQ12HJ8R2	FUSIBLE	0.5W	5%	8R2 Ω
R703	ERG2FJ821	METAL	2W	5%	820 Ω
R704	ERJ6GEYJ563	S.M.CARB	0.1W	5%	56K Ω
R705	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R706	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R707	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω
R708	ERJ6GEYJ393	S.M.CARB	0.1W	5%	39K Ω
R709	ERJ6GEYJ393	S.M.CARB	0.1W	5%	39K Ω
R710	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R711	ERG1SJ101	METAL	1W	5%	100 Ω
R712	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R803	ERC12ZGK335D	SOLID	0.5W	10%	3M3 Ω
R805	ERD25TJ473	CARBON	0.25W	5%	47K Ω
R806	ERD25TJ100	CARBON	0.25W	5%	10 Ω
R807	ERD25TJ332	CARBON	0.25W	5%	3K3 Ω
R809	ERD25TJ681	CARBON	0.25W	5%	680 Ω
R810	ERW2PKR27	WOUND	2W	10%	R27 Ω
R811	ERW2PKR27	WOUND	2W	10%	R27 Ω
R812	ERD75TAJ825	CARBON	0.75W	5%	8M2 Ω
R813	ERF7ZK2R7	WOUND	7W	20%	2R7 Ω
R814	ERD25TJ473	CARBON	0.25W	5%	47K Ω
R815	ERD25TJ222	CARBON	0.25W	5%	2K2 Ω
R850	ERD25TJ122	CARBON	0.25W	5%	1K2 Ω
R852	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R853	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R854	ERG2FJ223	METAL	2W	5%	22K Ω
R855	ERJ6GEYJ752	S.M.CARB	0.1W	5%	7K5 Ω
R857	ERJ6GEYJ752	S.M.CARB	0.1W	5%	7K5 Ω
R858	ERJ6GEYJ752	S.M.CARB	0.1W	5%	7K5 Ω
R859	ERJ6GEYJ753	S.M.CARB	0.1W	5%	75K Ω
R860	ERQ1CJP2R2	FUSIBLE	1W	10%	2R2 Ω
R861	ERD25TJ221	CARBON	0.25W	5%	220 Ω
R862	ERD25TJ272	CARBON	0.25W	5%	2K7 Ω
R863	ERDS1TJ560	CARBON	0.5W	5%	56 Ω
R864	ERDS1TJ151	CARBON	0.5W	5%	150 Ω
R865	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R867	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R868	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R869	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R870	ERJ6GEYJ272	S.M.CARB	0.1W	5%	2K7 Ω
R871	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R872	ERG1SJ183	METAL	1W	5%	18K Ω
R873	ERG1SJ223	METAL	1W	5%	22K Ω
R874	ERD25TJ104	CARBON	0.25W	5%	100K Ω
R876	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R877	ERW2PKR47	WOUND	2W	10%	R47 Ω
R878	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R913	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R914	ERJ6GEYJ822	S.M.CARB	0.1W	5%	8K2 Ω
R915	ERJ6GEYJ152	S.M.CARB	0.1W	5%	1K5 Ω
R916	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω
R919	ERQ14AJW390	FUSIBLE	0.25W	5%	39 Ω
R920	ERQ14AJW390	FUSIBLE	0.25W	5%	39 Ω
R921	ERD25TJ471	CARBON	0.25W	5%	470 Ω
R922	ERD25TJ393	CARBON	0.25W	5%	39K Ω
R923	ERD25TJ393	CARBON	0.25W	5%	39K Ω

Cct Ref	Parts Number	Description			
R924	ERDS1FJ390	CARBON	0.5W	5%	39 Ω
R925	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R926	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R927	ERD25TJ471	CARBON	0.25W	5%	470 Ω
R928	ERD25TJ5R6	CARBON	0.25W	5%	5R6 Ω
R929	ERDS1FJ471	CARBON	0.5W	5%	470 Ω
R930	ERD25TJ5R6	CARBON	0.25W	5%	5R6 Ω
R931	ERDS1FJ390	CARBON	0.5W	5%	39 Ω
R935	ERQ14AJW3R9	FUSIBLE	0.25W	5%	3R9 Ω
R936	ERQ1CJP331	FUSIBLE	1W	5%	330 Ω
R951	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω
R952	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R953	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R954	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω
R1051	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R1062	ERJ6GEYJ271	S.M.CARB	0.1W	5%	270 Ω
R1063	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R1101	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1102	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R1103	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R1104	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R1105	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1106	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R1107	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R1108	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R1109	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1110	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1111	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R1112	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R1113	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1114	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1115	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R1116	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1117	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1118	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1119	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1120	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1121	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1123	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1125	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1126	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1127	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1128	ERJ6GEYJ682	S.M.CARB	0.1W	5%	6K8 Ω
R1129	ERJ6GEYJ682	S.M.CARB	0.1W	5%	6K8 Ω
R1130	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R1131	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R1132	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1133	ERJ6GEYJ272	S.M.CARB	0.1W	5%	2K7 Ω
R1136	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R1137	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1138	ERJ6GEYJ105	S.M.CARB	0.1W	5%	1M Ω
R1139	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R1140	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R1141	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R1145	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1146	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1147	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1148	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1149	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R1151	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1152	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1156	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R1157	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R1158	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1159	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1160	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω

Cct Ref	Parts Number	Description			
R1161	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R1163	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1164	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1165	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1166	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1167	ERJ6GEYJ100	S.M.CARB	0.1W	5%	10 Ω
R1168	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R1169	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1170	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R1171	ERJ6GEYJ224	S.M.CARB	0.1W	5%	220K Ω
R1172	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R1173	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R1174	ERJ6GEYJ221	S.M.CARB	0.1W	5%	220 Ω
R1175	ERJ6GEYJ225	S.M.CARB	0.1W	5%	2M2 Ω
R1178	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R1180	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1251	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R1252	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R1253	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R1254	ERJ6GEYJ512	S.M.CARB	0.1W	5%	5K1 Ω
R1255	ERJ6GEYJ912	S.M.CARB	0.1W	5%	9K1 Ω
R1900	ERQ12HJ150	FUSIBLE	0.1W	5%	15 Ω 
R1901	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R1902	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R1903	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R1904	ERDS1TJ2R2	CARBON	0.5W	5%	2R2 Ω
R1905	ERJ6GEYJ224	S.M.CARB	0.1W	5%	220K Ω
R1906	ERJ6GEYJ753	S.M.CARB	0.1W	5%	75K Ω
R1907	ERJ6GEYJ753	S.M.CARB	0.1W	5%	75K Ω
R1908	ERJ6GEYJ154	S.M.CARB	0.1W	5%	150K Ω
R1909	ERDS1TJ2R2	CARBON	0.5W	5%	2R2 Ω
R1910	ERDS1TJ8R2	CARBON	0.5W	5%	8R2 Ω
R1911	ERDS1TJ8R2	CARBON	0.5W	5%	8R2 Ω
R1912	ERC12ZGK335D	SOLID	0.5W	10%	3M3 Ω
R2101	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2102	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2103	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2109	ERJ6GEYJ183	S.M.CARB	0.1W	5%	18K Ω
R2110	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R2111	ERJ6GEYJ221	S.M.CARB	0.1W	5%	220 Ω
R2112	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2113	ERJ6GEYJ562	S.M.CARB	0.1W	5%	5K6 Ω
R2114	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2115	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2116	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2117	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2118	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2119	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2120	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2200	ERJ6GEYJ183	S.M.CARB	0.1W	5%	18K Ω
R2201	ERJ6GEYJ563	S.M.CARB	0.1W	5%	56K Ω
R2203	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2204	ERJ6GEYJ822	S.M.CARB	0.1W	5%	8K2 Ω
R2205	ERJ6GEYJ562	S.M.CARB	0.1W	5%	5K6 Ω
R2206	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2207	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R2208	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2209	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2210	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R2211	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2212	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω
R2213	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R2214	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2215	ERJ6GEYJ822	S.M.CARB	0.1W	5%	8K2 Ω
R2220	ERJ6GEYJ183	S.M.CARB	0.1W	5%	18K Ω
R2221	ERJ6GEYJ563	S.M.CARB	0.1W	5%	56K Ω

Cct Ref	Parts Number	Description			
R2223	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2224	ERJ6GEYJ822	S.M.CARB	0.1W	5%	8K2 Ω
R2225	ERJ6GEYJ562	S.M.CARB	0.1W	5%	5K6 Ω
R2226	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2227	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R2228	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2229	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2230	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R2231	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2232	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω
R2233	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R2234	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2235	ERJ6GEYJ822	S.M.CARB	0.1W	5%	8K2 Ω
R2302	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2303	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2304	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2305	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2306	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2308	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2309	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2310	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2311	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2312	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2401	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R2402	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R2403	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2404	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2405	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2406	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2407	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2408	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2409	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2410	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2411	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2412	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2413	ERJ6GEYJ562	S.M.CARB	0.1W	5%	5K6 Ω
R2414	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2415	ERJ6GEYJ682	S.M.CARB	0.1W	5%	6K8 Ω
R2416	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R2417	ERJ6GEYJ821	S.M.CARB	0.1W	5%	820 Ω
R2418	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R2419	ERJ6GEYJ470	S.M.CARB	0.1W	5%	47 Ω
R2420	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2421	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R2422	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2423	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2424	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2425	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2426	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2427	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2428	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2429	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2430	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R2431	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2432	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2436	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2437	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2438	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2439	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2440	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2441	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2442	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2445	ERJ6GEYJ183	S.M.CARB	0.1W	5%	18K Ω
R2446	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2448	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2449	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω

Cct Ref	Parts Number	Description			
R2450	ERJ6GEYJ183	S.M.CARB	0.1W	5%	18K Ω
R2451	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2454	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2455	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2463	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2464	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2475	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2476	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2477	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R2478	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2479	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2480	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2481	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2482	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2483	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2484	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2485	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2486	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2487	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2488	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2489	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2490	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2491	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2492	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2493	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R2498	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2499	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R2505	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2506	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2507	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2508	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R2509	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R2510	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2511	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2512	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2513	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2514	ERJ6GEYJ222	S.M.CARB	0.1W	5%	2K2 Ω
R2515	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2516	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2517	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω
R2518	ERJ6GEYJ183	S.M.CARB	0.1W	5%	18K Ω
R2519	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω
R2520	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2521	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2523	ERJ6GEYJ681	S.M.CARB	0.1W	5%	680 Ω
R2524	ERJ6GEYJ681	S.M.CARB	0.1W	5%	680 Ω
R2525	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2526	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω
R2527	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2528	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2529	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2530	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2531	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2532	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2533	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2534	ERJ6GEYJ473	S.M.CARB	0.1W	5%	47K Ω
R2535	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2536	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R2537	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R2702	ERDS1TJ154	CARBON	0.5W	5%	150 Ω
R2703	ERDS1TJ184	CARBON	0.5W	5%	180 Ω
R2704	ERG5FJ473	METAL	5W	5%	47K Ω
R2705	ERD2FCVJ4R7P	CARBON	2W	5%	4R7 Ω
R2706	ERG1FJ101P	METAL	1W	5%	100 Ω
R2707	ERG1FJ101P	METAL	1W	5%	100 Ω
R2708	ERD2FCVJ4R7P	CARBON	2W	5%	4R7 Ω

Cct Ref	Parts Number	Description			
R2709	ERW12PKR33	WOUND	0.5W	10%	R33 Ω
R2712	ERG3FJ101	METAL	3W	5%	100 Ω
R2713	ERG3FJ101	METAL	3W	5%	100 Ω
R2714	ERDS1TJ2R2	CARBON	0.5W	5%	2R2 Ω
R2715	ERD25TJ101	CARBON	0.25W	5%	100 Ω
R2716	ERD25TJ202	CARBON	0.25W	5%	2K Ω
R2717	ERDS1TJ103	CARBON	0.5W	5%	10K Ω
R2725	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R2726	ERJ6GEYJ561	S.M.CARB	0.1W	5%	560 Ω
R2727	ERG3FJ471	METAL	3W	5%	470 Ω
R2728	ERG3FJ471	METAL	3W	5%	470 Ω
R2729	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω
R2730	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R2731	ERJ6GEYJ1R0	S.M.CARB	0.1W	5%	1 Ω
R2732	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R2733	ERJ6GEYJ331	S.M.CARB	0.1W	5%	330 Ω
R2734	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω
R2735	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R2736	ERJ6GEYJ1R0	S.M.CARB	0.1W	5%	1 Ω
R2738	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2739	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2740	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2741	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω
R2742	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R2743	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R3001	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3002	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R3003	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3004	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R3005	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3006	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R3007	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3008	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R3009	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3010	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3011	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3012	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3013	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3014	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R3015	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3016	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R3017	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3018	ERJ6GEYJ471	S.M.CARB	0.1W	5%	470 Ω
R3019	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3020	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R3021	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3022	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω
R3023	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω
R3024	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω
R3025	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3026	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3044	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3046	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3047	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3048	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R3049	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3050	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω
R3057	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω
R3204	ERG2SJS151	METAL	2W	5%	150 Ω
R3205	ERG2SJS151	METAL	2W	5%	150 Ω
R3207	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3208	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R3209	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω
R3210	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω
R3211	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω
R3212	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω

Cct Ref	Parts Number	Description							
R3213	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3214	ERJ6GEYJ683	S.M.CARB	0.1W	5%	68K Ω				
R3215	ERJ6GEYJ302	S.M.CARB	0.1W	5%	3K Ω				
R3216	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω				
R3217	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω				
R3218	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω				
R3219	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3220	ERJ6GEYJ683	S.M.CARB	0.1W	5%	68K Ω				
R3221	ERJ6GEYJ302	S.M.CARB	0.1W	5%	3K Ω				
R3222	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω				
R3223	ERJ6GEYJ223	S.M.CARB	0.1W	5%	22K Ω				
R3224	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3225	ERJ6GEYJ683	S.M.CARB	0.1W	5%	68K Ω				
R3226	ERJ6GEYJ302	S.M.CARB	0.1W	5%	3K Ω				
R3227	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3228	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω				
R3229	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3230	ERJ6GEYJ302	S.M.CARB	0.1W	5%	3K Ω				
R3231	ERJ6GEYJ122	S.M.CARB	0.1W	5%	1K2 Ω				
R3232	ERJ6GEYJ242	S.M.CARB	0.1W	5%	2K4 Ω				
R3233	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω				
R3234	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3402	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω				
R3403	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3404	ERJ6GEYJ242	S.M.CARB	0.1W	5%	2K4 Ω				
R3405	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω				
R3406	ERJ6GEYJ301	S.M.CARB	0.1W	5%	300 Ω				
R3407	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω				
R3408	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω				
R3409	ERJ6GEYJ750	S.M.CARB	0.1W	5%	75 Ω				
R3601	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3602	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3603	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3604	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3605	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3606	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3607	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω				
R3608	ERJ6GEYJ752	S.M.CARB	0.1W	5%	7K5 Ω				
R3609	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω				
R3610	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3613	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω				
R3614	ERJ6GEYJ391	S.M.CARB	0.1W	5%	390 Ω				
R3918	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω				
R3919	ERJ6GEYJ273	S.M.CARB	0.1W	5%	27K Ω				
R3920	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3921	ERJ6GEYJ153	S.M.CARB	0.1W	5%	15K Ω				
R3922	EVMEASA00B53	CONTROL			5K Ω				
R3923	ERJ6GEYJ562	S.M.CARB	0.1W	5%	5K6 Ω				
R3925	ERO25CKF1272	METAL	0.25W	5%	2K7 Ω				
R3926	ERO25CKF3242	METAL	0.25W	5%	2K4 Ω				
R3927	ERD25TJ103	CARBON	0.25W	5%	10K Ω				
R3928	ERDS1FJ103	CARBON	0.5W	5%	10K Ω				
R3929	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω				
R3930	ERDS1FJ103	CARBON	0.5W	5%	10K Ω				
R3931	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω				
R3932	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3933	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3934	ERJ6GEYJ125	S.M. CAR	0.1W	5%	1M2 Ω				
R3935	ERDS1FJ561	CARBON	0.5W	5%	56 Ω				
R3936	ERJ6GEYJ820	S.M.CARB	0.1W	5%	82 Ω				
R3938	EVMEASA00B53	CONTROL			5K Ω				
R3939	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω				
R3941	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3942	ERD25TJ562	CARBON	0.25W	5%	5K6 Ω				
R3943	ERDS1TJ104	CARBON	0.5W	5%	100K Ω				
R3944	ERJ6GEYJ125	S.M. CAR	0.1W	5%	1M2 Ω				
R3945	ERJ6GEYJ125	S.M. CAR	0.1W	5%	1M2 Ω				
R3946	ERJ6GEYJ104	S.M.CARB	0.1W	5%	100K Ω				
R3947	ERG2FJ123H	METAL	2W	5%	12K Ω				
R3949	ERDS1FJ332	CARBON	0.5W	5%	3K3 Ω				
R3950	ERG3FJ102H	METAL	3W	5%	1K Ω				
R3951	ERD25TJ334	CARBON	0.25W	5%	330K Ω				
R3952	ERJ6GEYJ101	S.M.CARB	0.1W	5%	100 Ω				
R3953	ERG2FJ100H	METAL	2W	5%	10 Ω				
R3954	ERD25TJ473	CARBON	0.25W	5%	47K Ω				
R3955	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω				
R3956	ERD25TJ104	CARBON	0.25W	5%	100K Ω				
R3957	ERD25TJ104	CARBON	0.25W	5%	100K Ω				
R3958	ERD25TJ104	CARBON	0.25W	5%	100K Ω				
R3959	ERD25TJ104	CARBON	0.25W	5%	100K Ω				
R3960	ERJ6GEYJ622	S.M.CARB	0.1W	5%	6K2 Ω				
R3961	ERJ6GEYJ562	S.M.CARB	0.1W	5%	5K6 Ω				
R3962	ERD25TJ563	CARBON	0.25W	5%	56K Ω				
R3963	ERJ6GEYJ563	S.M.CARB	0.1W	5%	56K Ω				
R3972	ERG2FJ471	METAL	2W	5%	470 Ω				
R3973	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3974	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3975	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3976	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3978	ERJ6GEY0R00	S.M.CARB	0.1W	5%	0 Ω				
R3981	ERQ14AJ220	FUSIBLE	0.25W	5%	22 Ω				
R3982	ERJ6GEYJ333	S.M.CARB	0.1W	5%	33K Ω				
R3983	ERJ6GEYJ823	S.M.CARB	0.1W	5%	82K Ω				
R3984	ERJ6GEYJ123	S.M.CARB	0.1W	5%	12K Ω				
R3985	ERJ6GEYJ102	S.M.CARB	0.1W	5%	1K Ω				
R3986	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3987	ERJ6GEYJ332	S.M.CARB	0.1W	5%	3K3 Ω				
R3988	ERJ6GEYJ684	S.M.CARB	0.1W	5%	680K Ω				
R3989	ERJ6GEYJ221	S.M.CARB	0.1W	5%	220 Ω				
R3990	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3991	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3992	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
R3993	ERJ6GEYJ472	S.M.CARB	0.1W	5%	4K7 Ω				
R3994	ERJ6GEYJ103	S.M.CARB	0.1W	5%	10K Ω				
CAPACITORS									
C102	ECJ2VF1H103Z	ELECT	350V		10nF				
C103	ECJ2VF1H104Z	ELECT	350V		100nF				
C106	ECUV1H560JCX	S.M. CAP	50V		56pF				
C107	ECJ2VF1H104Z	ELECT	350V		100nF				
C108	ECA1CM100GB	ELECT	16V		10 μ F				
C109	ECUV1H102JCX	S.M. CAP	50V		1nF				
C110	ECJ2VF1H103Z	ELECT	350V		10nF				
C111	ECA1HMR33GB	ELECT	50V		0.33 μ F				
C117	ECJ2VF1H103Z	ELECT	350V		10nF				
C118	ECJ2VF1H104Z	ELECT	350V		100nF				
C119	ECA1CM221GB	ELECT	16V		220 μ F				
C120	ECA1CM221GB	ELECT	16V		220 μ F				
C121	ECUV1H561KBX	S.M. CAP	50V		560pF				
C124	ECUV1H220JCX	S.M. CAP	50V		22pF				
C125	ECUV1H100DCX	S.M. CAP	50V		10pF				
C251	ECA1CM470GB	ELECT	16V		47 μ F				
C252	ECUV1H103KBX	S.M. CAP	50V		10nF				
C253	ECA1HM4R7GB	ELECT	50V		4.7 μ F				
C254	ECQM1H684J	FILM	50V		680nF				
C255	ECA1EM101GB	ELECT	25V		100 μ F				
C256	ECUV1H103KBX	S.M. CAP	50V		10nF				
C257	ECA1HM4R7GB	ELECT	50V		4.7 μ F				
C258	ECA1CM470GB	ELECT	16V		47 μ F				
C259	ECQM1H684J	FILM	50V		680nF				
C260	ECA1VM102GB	ELECT	35V		1nF				
C261	ECA1VM102GB	ELECT	35V		1nF				
C263	ECA1HM010GB	ELECT	50V		1 μ F				

Cct Ref	Parts Number	Description		
C264	ECA1HHG222E	ELECT	50V	2200µF
C266	ECA1HM010GB	ELECT	50V	1µF
C267	ECJ2VB1H104K	ELECT	350V	100nF
C268	ECJ2VB1H104K	ELECT	350V	100nF
C270	ECJ2VB1H104K	ELECT	350V	100nF
C301	ECJ2VB1C104K	ELECT	350V	100nF
C302	ECJ2VB1C104K	ELECT	350V	100nF
C303	ECJ2VB1C104K	ELECT	350V	100nF
C304	ECA1CM100GB	ELECT	16V	10µF
C351	ECUV1H090DCN	S.M. CAP	50V	90pF
C352	ECUV1H090DCN	S.M. CAP	50V	90pF
C353	ECUV1H090DCN	S.M. CAP	50V	90pF
C354	ECQM2104KZ	FILM	250V	100nF
C355	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C356	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C357	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C358	ECQM1H224J	FILM	50V	220nF
C360	ECKC3D272JB	CERAMIC	2KV	2.7nF
C361	ECA1HMR47GB	ELECT	50V	0.47µF
C363	ECA1VM471GB	ELECT	35V	470µF
C364	ECJ2VF1H103Z	ELECT	350V	10nF
C366	ECA1CM100GB	ELECT	16V	10µF
C451	ECUV1H102JX	S.M. CAP	50V	1nF
C453	ECUV1H152KBX	S.M. CAP	50V	1.5pF
C454	ECUV1H223KBM	S.M. CAP	50V	22nF
C455	ECA1HM100GB	ELECT	50V	10µF
C456	ECA1HHG221B	ELECT	50V	220µF
C458	ECQB1222JF3	FILM	100V	2.2nF
C459	222236516154	FILM	160V	150nF
C461	ECCR2H270J	CERAMIC	500V	27pF
C508	ECQV1H105JZ	FILM	50V	1µF
C509	ECA1VM470B	ELECT	35V	47µF
C510	ECUV1H104KBX	S.M. CAP	50V	100nF
C511	ECQM2683JZ	FILM	250V	68nF
C512	ECKC2H472J	CERAMIC	500V	4.7nF
C551	ECKC3D681J	CERAMIC	2KV	680pF
C552	ECWH15H102JN	FILM	1500V	1nF
C556	ECQF6303JZ	FILM	630V	30nF
C557	ECKC2H471J	CERAMIC	500V	470pF
C558	ECA1HHG471E	ELECT	50V	470µF
C561	ECA1EHG102B	ELECT	25V	1000µF
C562	ECKC2H101J	CERAMIC	500V	100pF
C563	ECA2EHG220B	ELECT	250V	20µF
C564	ECEA2AU2R2	ELECT	100V	2.2µF
C565	ECQP1H273J	FILM	100V	2700µF
C566	ECKC2H471J	CERAMIC	500V	470pF
C567	ECA1EHG102B	ELECT	25V	1000µF
C568	ECKC2H471J	CERAMIC	500V	470pF
C569	ECKC2H102J	CERAMIC	500V	1nF
C570	ECUV1H221JCX	S.M. CAP	50V	220pF
C571	ECUV1H221JCX	S.M. CAP	50V	220pF
C580	ECQE2334B120	FILM	250V	330nF
C581	ECWF2H514J	FILM	500V	510nF
C582	ECWF2824JBB	FILM	200V	820nF
C583	ECWH15H562JN	FILM	1500V	5.6nF
C584	ECWH15H562JN	FILM	1500V	5.6nF
C585	ECUV1H103KBX	S.M. CAP	50V	10nF
C586	ECWF2H224J	FILM	500V	220nF
C601	ECUV1H104KBX	S.M. CAP	50V	100nF
C602	ECA1HM101GB	ELECT	50V	100µF
C603	ECUV1H102JCX	S.M. CAP	50V	1nF
C604	ECJ2VF1H223Z	ELECT	350V	22nF
C605	ECA1HM101GB	ELECT	50V	100µF
C606	ECA1HM3R3GB	ELECT	50V	3.3µF
C607	ECJ2VF1H104Z	ELECT	350V	100nF
C608	ECUV1H153KBX	S.M. CAP	50V	15nF

Cct Ref	Parts Number	Description		
C609	ECUV1H153KBX	S.M. CAP	50V	15nF
C610	ECUV1H153KBX	S.M. CAP	50V	15nF
C611	ECUV1H153KBX	S.M. CAP	50V	15nF
C612	ECUV1H153KBX	S.M. CAP	50V	15nF
C613	ECUV1H153KBX	S.M. CAP	50V	15nF
C614	ECUV1H050CCX	S.M. CAP	50V	50pF
C615	ECUV1H050CCX	S.M. CAP	50V	50pF
C616	ECA1HM101GB	ELECT	50V	100µF
C617	ECUV1H223KBX	S.M. CAP	50V	22nF
C618	ECA1CM221GB	ELECT	16V	220µF
C619	ECJ2VB1H473K	ELECT	350V	47nF
C620	ECA1HM101GB	ELECT	50V	100µF
C621	ECJ2VB1C104K	ELECT	350V	100nF
C622	ECUV1H683KBX	S.M. CAP	50V	68nF
C623	ECUV1H102JCX	S.M. CAP	50V	1nF
C624	ECJ3VB1C474K	ELECT	3.5KV	470nF
C625	ECJ3VB1C474K	ELECT	3.5KV	470nF
C626	ECJ3VB1C474K	ELECT	3.5KV	470nF
C627	ECJ3VB1C474K	ELECT	3.5KV	470nF
C628	ECA1CM100GB	ELECT	16V	10µF
C629	ECUV1H104KBX	S.M. CAP	50V	100nF
C630	ECUV1H100DCX	S.M. CAP	50V	10pF
C631	ECUV1H683ZFX	S.M. CAP	50V	68nF
C633	ECUV1H271JCX	S.M. CAP	50V	270pF
C634	ECUV1H271JCX	S.M. CAP	50V	270pF
C635	ECUV1H180JCX	S.M. CAP	50V	18pF
C636	ECUV1H271JCX	S.M. CAP	50V	270pF
C637	ECUV1H101JCX	S.M. CAP	50V	100pF
C638	ECUV1H471JCX	S.M. CAP	50V	470pF
C639	ECUV1H332KBM	S.M. CAP	50V	3.3nF
C701	ECA1HHG101B	ELECT	50V	100µF
C702	ECUV1H103KBX	S.M. CAP	50V	10nF
C703	ECEA1HGE100	ELECT	50V	10µF
C704	ECQB1H223K	FILM	50V	22nF
C705	ECQB1H222J	FILM	50V	2.2nF
C804	222233510224	FILM	250V	220nF
C806	ECKWNA101MBC	CERAMIC	400V	100µF
C807	ECKC2H472J	CERAMIC	500V	4.7nF
C808	ECKC2H472J	CERAMIC	500V	4.7nF
C809	ECKC2H472J	CERAMIC	500V	4.7nF
C810	ECKC2H472J	CERAMIC	500V	4.7nF
C811	ECOS2GA221CA	ELECT	400V	220µF
C814	ECKC3D102J	CERAMIC	2KV	1nF
C815	ECKC1H471J	CERAMIC	50V	470pF
C816	EEUFC1E820B	CERAMIC	25V	82pF
C817	ECQE6104K	FILM	600V	100nF
C818	ECKWNA332MEC	CERAMIC	250V	3.3nF
C819	ECQB1H152K	FILM	50V	1.5nF
C850	ECKC3D471JB	CERAMIC	2KV	470pF
C851	ECA2CM221E	ELECT	160V	220µF
C852	ECA2CHG101E	ELECT	160V	100µF
C853	ECKC2H471J	CERAMIC	500V	470pF
C854	ECA1EM102GB	ELECT	25V	100µF
C855	ECKC2H471J	CERAMIC	500V	470pF
C856	ECA1AHG222B	ELECT	10V	2200µF
C857	ECKC2H471J	CERAMIC	500V	470pF
C858	ECEA1HGE102	ELECT	50V	1000µF
C859	ECJ2VF1H104Z	ELECT	350V	100nF
C860	ECA1HM101GB	ELECT	50V	100µF
C862	ECJ2VF1H104Z	ELECT	350V	100nF
C863	ECA1HM101GB	ELECT	50V	100µF
C866	ECJ2VF1H104Z	ELECT	350V	100nF
C867	ECA1CM100GB	ELECT	16V	10µF
C868	ECA1CM100GB	ELECT	16V	10µF
C869	ECA1EM101GB	ELECT	25V	100µF
C870	ECA1EM471GB	ELECT	25V	470µF

Cct Ref	Parts Number	Description		
C871	ECA1CM102B	ELECT	16V	1000µF
C872	ECA1CM471GB	ELECT	16V	470µF
C873	ECA1CM100GB	ELECT	16V	10µF
C875	ECA2CM4R7B	ELECT	160V	10µF
C876	ECA1AHG471E	ELECT	10V	470pF
C902	ECA1VM101GB	ELECT	35V	100µF
C903	ECUV1H472KBX	S.M. CAP	50V	4.7nF
C904	ECUV1H472KBX	S.M. CAP	50V	4.7nF
C906	ECUV1H471KBX	S.M. CAP	50V	470pF
C908	ECUV1H151JCX	S.M. CAP	50V	150pF
C909	ECKC2H472J	CERAMIC	500V	4.7nF
C910	ECKC2H472J	CERAMIC	500V	4.7nF
C911	ECUV1H151JCX	S.M. CAP	50V	150pF
C912	ECEA2CU100	ELECT	160V	10µF
C913	ECA1HM101GB	ELECT	50V	100µF
C914	ECA1HM101GB	ELECT	50V	100µF
C916	ECEA2CGE100	ELECT	160V	10µF
C950	ECJ2VB1C104K	ELECT	350V	100nF
C1061	ECUV1H103KBX	S.M. CAP	50V	10nF
C1062	ECA1HM101GB	ELECT	50V	100µF
C1063	ECUV1H331JCX	S.M. CAP	50V	330pF
C1101	ECJ2VF1H104Z	ELECT	350V	100nF
C1102	ECA0JM101G	ELECT	6.3V	100µF
C1103	ECUV1H220JCX	S.M. CAP	50V	22pF
C1104	ECUV1H220JCX	S.M. CAP	50V	22pF
C1105	ECUV1H101JCX	S.M. CAP	50V	100pF
C1106	ECKC2H681J	CERAMIC	500V	680pF
C1108	ECJ2VB1H333K	ELECT	350V	33nF
C1111	ECA1CM100GB	ELECT	16V	10µF
C1112	ECUV1H103KBX	S.M. CAP	50V	10nF
C1115	ECJ3VB1C474K	ELECT	3.5KV	470nF
C1116	ECUV1H472KBX	S.M. CAP	50V	4.7nF
C1117	ECJ2VF1H104Z	ELECT	350V	100nF
C1118	ECUV1H103KBX	S.M. CAP	50V	10nF
C1119	ECUV1H221JCX	S.M. CAP	50V	220pF
C1120	ECJ2VF1H104Z	ELECT	350V	100nF
C1121	ECUV1H221JCX	S.M. CAP	50V	220pF
C1123	ECUV1H471JCX	S.M. CAP	50V	470pF
C1124	ECUV1H391JCX	S.M. CAP	50V	390pF
C1125	ECUV1H391JCX	S.M. CAP	50V	390pF
C1126	ECUV1H391JCX	S.M. CAP	50V	390pF
C1127	ECUV1H221JCX	S.M. CAP	50V	220pF
C1129	ECUV1H270JCX	S.M. CAP	50V	27pF
C1900	ECQB1H153K	FILM	50V	15nF
C1901	ECUV1H103KBX	S.M. CAP	50V	10nF
C1903	ECA1EM470GB	ELECT	25V	47µF
C1904	ECQB1H104J	FILM	50V	100nF
C1905	ECQB1H104J	FILM	50V	100nF
C1906	ECQE2A474MWB	FILM	250V	470nF
C1909	ECUV1H103KBX	S.M. CAP	50V	10nF
C2101	ECUV1H102JCX	S.M. CAP	50V	1nF
C2102	ECUV1H102JCX	S.M. CAP	50V	1nF
C2103	ECUV1H102JCX	S.M. CAP	50V	1nF
C2104	ECUV1H102JCX	S.M. CAP	50V	1nF
C2105	ECUV1H102JCX	S.M. CAP	50V	1nF
C2106	ECUV1H102JCX	S.M. CAP	50V	1nF
C2107	ECUV1H102JCX	S.M. CAP	50V	1nF
C2108	ECUV1H102JCX	S.M. CAP	50V	1nF
C2109	ECUV1H102JCX	S.M. CAP	50V	1nF
C2110	ECUV1H102JCX	S.M. CAP	50V	1nF
C2111	ECA1CM100GB	ELECT	16V	10µF
C2112	ECA1CM100GB	ELECT	16V	10µF
C2113	ECA1HM3R3GB	ELECT	50V	3.3µF
C2114	ECJ2VF1H104Z	ELECT	350V	100nF
C2115	ECUV1H221JCX	S.M. CAP	50V	220pF
C2116	ECUV1H221JCX	S.M. CAP	50V	220pF

Cct Ref	Parts Number	Description		
C2117	ECUV1H221JCX	S.M. CAP	50V	220pF
C2118	ECUV1H221JCX	S.M. CAP	50V	220pF
C2119	ECUV1H221JCX	S.M. CAP	50V	220pF
C2120	ECUV1H221JCX	S.M. CAP	50V	220pF
C2121	ECA1CM100GB	ELECT	16V	10µF
C2122	ECJ2VF1H104Z	ELECT	350V	100nF
C2123	ECUV1H221JCX	S.M. CAP	50V	220pF
C2124	ECUV1H070DTX	S.M. CAP	50V	70pF
C2125	ECUV1H470JCX	S.M. CAP	50V	47pF
C2126	ECUV1H070DTX	S.M. CAP	50V	70pF
C2127	ECUV1H010CCX	S.M. CAP	50V	1pF
C2128	ECUV1H010CCX	S.M. CAP	50V	1pF
C2129	ECA1CM102B	ELECT	16V	1000µF
C2130	ECA1CM331B	ELECT	16V	330µF
C2131	ECJ2VF1H103Z	ELECT	350V	10nF
C2132	ECJ2VF1H103Z	ELECT	350V	10nF
C2134	ECJ2VF1H103Z	ELECT	350V	10nF
C2135	ECA1HM101GB	ELECT	50V	100µF
C2136	ECJ2VF1H104Z	ELECT	350V	100nF
C2137	ECA1CM100GB	ELECT	16V	10µF
C2138	ECUV1H471KBX	S.M. CAP	50V	470pF
C2139	ECUV1H221JCX	S.M. CAP	50V	220pF
C2140	ECA1HM101GB	ELECT	50V	100µF
C2141	ECUV1H152JCX	S.M. CAP	50V	1.5pF
C2200	ECUV1H562KBX	S.M. CAP	50V	5.6nF
C2201	ECA1HM100GB	ELECT	50V	10µF
C2203	ECA1VM470B	ELECT	35V	47µF
C2204	ECA1HM4R7GB	ELECT	50V	4.7µF
C2205	ECUV1H562KBX	S.M. CAP	50V	5.6nF
C2206	ECA1HM100GB	ELECT	50V	10µF
C2207	ECUV1H332KBX	S.M. CAP	50V	3.3nF
C2208	ECUV1H104KBX	S.M. CAP	50V	100nF
C2209	ECUV1H681JCX	S.M. CAP	50V	680pF
C2211	ECUV1C104KBX	S.M. CAP	16V	100nF
C2212	ECUV1C104KBX	S.M. CAP	16V	100nF
C2215	ECUV1H103KBX	S.M. CAP	50V	10nF
C2220	ECUV1H562KBX	S.M. CAP	50V	5.6nF
C2221	ECA1HM100GB	ELECT	50V	10µF
C2223	ECA1VM470B	ELECT	35V	47µF
C2224	ECA1HM4R7GB	ELECT	50V	4.7µF
C2225	ECUV1H562KBX	S.M. CAP	50V	5.6nF
C2226	ECA1HM100GB	ELECT	50V	10µF
C2227	ECUV1H332KBX	S.M. CAP	50V	3.3nF
C2228	ECUV1H104KBX	S.M. CAP	50V	100nF
C2229	ECUV1H681JCX	S.M. CAP	50V	680pF
C2231	ECUV1C104KBX	S.M. CAP	16V	100nF
C2232	ECUV1C104KBX	S.M. CAP	16V	100nF
C2235	ECUV1H103KBX	S.M. CAP	50V	10nF
C2240	ECA1CM471GB	ELECT	16V	470µF
C2301	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C2302	ECA1CM470GB	ELECT	16V	47µF
C2303	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C2304	ECA1CM470GB	ELECT	16V	47µF
C2401	ECUV1H103KBX	S.M. CAP	50V	10nF
C2402	ECUV1H103KBX	S.M. CAP	50V	10nF
C2403	ECA1HM010GB	ELECT	50V	1µF
C2405	ECA1HM010GB	ELECT	50V	1µF
C2406	ECA1HM101GB	ELECT	50V	100µF
C2407	ECA1CM471GB	ELECT	16V	470µF
C2408	ECA1HM010GB	ELECT	50V	1µF
C2409	ECA1CM100GB	ELECT	16V	10µF
C2410	ECUV1H152KBX	S.M. CAP	50V	1.5pF
C2411	ECUV1H221JX	S.M. CAP	50V	220pF
C2412	ECUV1H471KBX	S.M. CAP	50V	470pF
C2413	ECUV1H102KBX	S.M. CAP	50V	1nF
C2414	ECUV1H102KBX	S.M. CAP	50V	1nF

Cct Ref	Parts Number	Description		
C2415	ECUV1H102KBX	S.M. CAP	50V	1nF
C2416	ECUV1H102KBX	S.M. CAP	50V	1nF
C2417	ECUV1H102KBX	S.M. CAP	50V	1nF
C2418	ECA1CM220GB	ELECT	16V	22μF
C2419	ECA1CM220GB	ELECT	16V	22μF
C2420	ECUV1H152KBX	S.M. CAP	50V	1.5pF
C2421	ECUV1H471KBX	S.M. CAP	50V	470pF
C2422	ECA1CM100GB	ELECT	16V	10μF
C2423	ECJ2VB1H104K	ELECT	350V	100nF
C2424	ECA1HM3R3GB	ELECT	50V	3.3μF
C2427	ECUV1H152KBX	S.M. CAP	50V	1.5pF
C2428	ECUV1H471KBX	S.M. CAP	50V	470pF
C2429	ECA1CM100GB	ELECT	16V	10μF
C2430	ECUV1H010CCX	S.M. CAP	50V	1pF
C2431	ECUV1H010CCX	S.M. CAP	50V	1pF
C2432	ECUV1H101JCX	S.M. CAP	50V	100pF
C2434	ECA1HM010GB	ELECT	50V	1μF
C2435	ECA1HM010GB	ELECT	50V	1μF
C2436	ECUV1H101JCX	S.M. CAP	50V	100pF
C2437	ECUV1H101JCX	S.M. CAP	50V	100pF
C2438	ECA1HM010GB	ELECT	50V	1μF
C2439	ECA1HM010GB	ELECT	50V	1μF
C2440	ECUV1H101JCX	S.M. CAP	50V	100pF
C2441	ECUV1H103KBX	S.M. CAP	50V	10nF
C2445	ECUV1H103KBX	S.M. CAP	50V	10nF
C2451	ECA1CM100GB	ELECT	16V	10μF
C2452	ECJ2VF1H104Z	ELECT	350V	100nF
C2453	ECA1HM010GB	ELECT	50V	1μF
C2454	ECUV1H222KBX	S.M. CAP	50V	2.2nF
C2455	ECA1HM010GB	ELECT	50V	1μF
C2456	ECUV1H222KBX	S.M. CAP	50V	2.2nF
C2457	ECA1HM010GB	ELECT	50V	1μF
C2458	ECUV1H222KBX	S.M. CAP	50V	2.2nF
C2459	ECA1HM010GB	ELECT	50V	1μF
C2460	ECUV1H222KBX	S.M. CAP	50V	2.2nF
C2461	ECA1HM010GB	ELECT	50V	1μF
C2462	ECUV1H222KBX	S.M. CAP	50V	2.2nF
C2467	ECUV1H103KBX	S.M. CAP	50V	10nF
C2468	ECA1HM010GB	ELECT	50V	1μF
C2469	ECA1HM010GB	ELECT	50V	1μF
C2470	ECA1CM100GB	ELECT	16V	10μF
C2471	ECJ2VB1H104K	ELECT	350V	100nF
C2472	ECUV1H102JCX	S.M. CAP	50V	1nF
C2474	ECA1CM470GB	ELECT	16V	47μF
C2475	ECA1HM010GB	ELECT	50V	1μF
C2476	ECA1HM010GB	ELECT	50V	1μF
C2477	ECA1HM010GB	ELECT	50V	1μF
C2478	ECA1HM010GB	ELECT	50V	1μF
C2479	ECUV1H101JCX	S.M. CAP	50V	100pF
C2480	ECUV1H101JCX	S.M. CAP	50V	100pF
C2481	ECA1HM101GB	ELECT	50V	100μF
C2482	ECA1HM101GB	ELECT	50V	100μF
C2483	ECA1CM470GB	ELECT	16V	47μF
C2484	ECUV1H103KBX	S.M. CAP	50V	10nF
C2707	ECOS2GA101BB	ELECT	400V	100μF
C2708	ECKC3D471JB	CERAMIC	2KV	470pF
C2709	ECKC2H103J	CERAMIC	50V	10nF
C2710	ECQM1H333J	FILM	50V	33nF
C2711	ECQM1H683J	FILM	50V	68nF
C2712	ECA1CM221GB	ELECT	16V	220μF
C2713	ECA1CM221GB	ELECT	16V	220μF
C2714	ECKCWS471J	CERAMIC	400V	470pF
C2715	ECKC2H471J	CERAMIC	500V	470pF
C2717	ECA1VHG331B	ELECT	35V	330pF
C2718	ECA1HHG471E	ELECT	50V	470μF
C2719	ECQM1H104J	FILM	50V	100nF

Cct Ref	Parts Number	Description		
C2733	ECA1HM010GB	ELECT	50V	1μF
C2734	ECUV1H101JCX	S.M. CAP	50V	100pF
C2735	ECA1HM330B	ELECT	50V	33μF
C2736	ECJ2VF1H103Z	ELECT	350V	10nF
C2737	ECA1VM102GB	ELECT	35V	1nF
C2738	ECUV1H222KBX	S.M. CAP	50V	2.2nF
C2739	ECA1VM102GB	ELECT	35V	1nF
C2740	ECJ2VF1H103Z	ELECT	350V	10nF
C2741	ECUV1H223KBX	S.M. CAP	50V	22nF
C2742	ECQM1H474J	FILM	50V	470nF
C2743	ECA1HM010GB	ELECT	50V	1μF
C2744	ECUV1H101JCX	S.M. CAP	50V	100pF
C2745	ECA1HM330B	ELECT	50V	33μF
C2746	ECJ2VF1H103Z	ELECT	350V	10nF
C2747	ECA1VM221B	ELECT	35V	220μF
C2748	ECUV1H222KBX	S.M. CAP	50V	2.2nF
C2749	ECA1VM101GB	ELECT	35V	100μF
C2750	ECJ2VF1H103Z	ELECT	350V	10nF
C2751	ECJ2VF1H683Z	ELECT	350V	68nF
C2752	ECQM1H474J	FILM	50V	470nF
C2753	ECUV1H103KBX	S.M. CAP	50V	10nF
C2755	ECUV1H103KBX	S.M. CAP	50V	10nF
C2756	ECA1CM220GB	ELECT	16V	22μF
C2758	ECQM1H474J	FILM	50V	470nF
C2759	ECQM1H474J	FILM	50V	470nF
C3001	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3002	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3003	ECA1CM470GB	ELECT	16V	47μF
C3005	ECUV1H561JCX	S.M. CAP	50V	560pF
C3006	ECJ3VB1C474K	ELECT	3.5KV	470nF
C3007	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3008	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3009	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3010	ECA1CM470GB	ELECT	16V	47μF
C3012	ECUV1H561JCX	S.M. CAP	50V	560pF
C3013	ECJ3VB1C474K	ELECT	3.5KV	470nF
C3014	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3015	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3016	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3017	ECA1CM470GB	ELECT	16V	47μF
C3019	ECUV1H561JCX	S.M. CAP	50V	560pF
C3020	ECJ3VB1C474K	ELECT	3.5KV	470nF
C3021	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3022	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3023	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3024	ECA1CM470GB	ELECT	16V	47μF
C3026	ECUV1H561JCX	S.M. CAP	50V	560pF
C3027	ECJ3VB1C474K	ELECT	3.5KV	470nF
C3028	ECUV1H222JCX	S.M. CAP	50V	2.2nF
C3029	ECA1HM101GB	ELECT	50V	100μF
C3032	ECUV1H271JCX	S.M. CAP	50V	270pF
C3033	ECUV1H271JCX	S.M. CAP	50V	270pF
C3034	ECUV1H271JCX	S.M. CAP	50V	270pF
C3035	ECUV1H271JCX	S.M. CAP	50V	270pF
C3101	ECUV1H104KBX	S.M. CAP	50V	100nF
C3102	ECUV1E104KBX	S.M. CAP	25V	100nF
C3111	ECUV1H391JCX	S.M. CAP	50V	390pF
C3112	ECUV1H271JCX	S.M. CAP	50V	270pF
C3201	ECUV1H103KBX	S.M. CAP	50V	10nF
C3202	ECUV1H103KBX	S.M. CAP	50V	10nF
C3203	ECUV1H561JCX	S.M. CAP	50V	560pF
C3204	ECUV1H561JCX	S.M. CAP	50V	560pF
C3205	ECA1HM470GB	ELECT	50V	47μF
C3206	ECUV1H561JCX	S.M. CAP	50V	560pF
C3207	ECUV1H561JCX	S.M. CAP	50V	560pF
C3208	ECA1HM470GB	ELECT	50V	47μF

Cct Ref	Parts Number	Description		
C3209	ECUV1H103KBX	S.M. CAP	50V	10nF
C3210	ECJ2VB1C104K	ELECT	350V	100nF
C3211	ECUV1H103KBX	S.M. CAP	50V	10nF
C3212	ECUV1H103KBX	S.M. CAP	50V	10nF
C3213	ECUV1H103KBX	S.M. CAP	50V	10nF
C3214	ECJ2VB1C104K	ELECT	350V	100nF
C3215	ECUV1H103KBX	S.M. CAP	50V	10nF
C3216	ECA1CM330GB	ELECT	16V	33pF
C3217	ECJ2VB1C104K	ELECT	350V	100nF
C3221	ECA1HM4R7GB	ELECT	50V	4.7µF
C3401	ECQM1H224J	FILM	50V	220nF
C3402	ECUV1H101JCX	S.M. CAP	50V	100pF
C3403	ECA1HM101GB	ELECT	50V	100µF
C3404	ECQM1H224J	FILM	50V	220nF
C3405	ECUV1H180JCX	S.M. CAP	50V	18pF
C3406	ECUV1H271JCX	S.M. CAP	50V	270pF
C3407	ECUV1H271JCX	S.M. CAP	50V	270pF
C3408	ECA1HM101GB	ELECT	50V	100µF
C3601	ECA1HM101GB	ELECT	50V	100µF
C3909	ECQB1H153K	FILM	50V	15nF
C3910	ECA1HM010GB	ELECT	50V	1µF
C3911	ECQB1H153K	FILM	50V	15nF
C3912	ECQM1472GZ	FILM	100V	4.7nF
C3913	ECQV1H105JZ	FILM	50V	1µF
C3914	ECA1CM331B	ELECT	16V	330µF
C3915	ECQB1H103J	FILM	50V	10nF
C3916	ECQM1H154J	FILM	50V	150nF
C3917	ECQM1H154J	FILM	50V	150nF
C3918	ECQB1H682K	FILM	50V	6.8nF
C3919	ECQB1H333J	FILM	50V	33nF
C3920	ECQB1H562K	FILM	50V	5.6nF
C3921	ECKC3A821J	CERAMIC	1KV	820pF
C3922	ECKC3A391J	CERAMIC	1KV	390pF
C3923	ECEA1HN100UB	ELECT	50V	10µF
C3924	ECKC3A182J	CERAMIC	1KV	1800pF
C3925	ECKC3A151J	CERAMIC	1KV	150pF
C3926	ECKC3A101J	CERAMIC	1KV	100pF
C3927	ECA1HM010GB	ELECT	50V	1µF
C3928	ECQM4223JZW	FILM	400V	22nF
C3929	ECQM4223JZW	FILM	400V	22nF
C3931	ECKC3D101J	CERAMIC	2KV	100pF
C3932	ECUV1H103KBX	S.M. CAP	50V	10nF
C3933	ECKC3A471J	CERAMIC	1KV	470pF
C3936	ECA2CM330B	ELECT	160V	33µF
C3937	ECQM1H104J	FILM	50V	100nF
C3939	ECA1HM3R3GB	ELECT	50V	3.3µF
C3940	ECA1CM471GB	ELECT	16V	470µF
C3941	ECA1HMR47GB	ELECT	50V	0.47µF
C3942	ECEA1HN010UB	ELECT	50V	1µF
C3943	ECUV1H101JCX	S.M. CAP	50V	100pF
C3944	ECQB1H103J	FILM	50V	10nF
C3945	ECA1HM100GB	ELECT	50V	10µF
C3946	ECQB1H333J	FILM	50V	33nF
C3947	ECKC3D102J	CERAMIC	2KV	1nF
C3948	ECQV1H105JZ	FILM	50V	1µF
C3949	ECQM1H684J	FILM	50V	680nF
C3950	ECUV1H104KBX	S.M. CAP	50V	100nF
C3951	ECA1HM101GB	ELECT	50V	100µF
C3952	ECWH15H102JN	FILM	1500V	1nF
C3953	ECQP1H473JZ3	FILM	100V	47nF
C3954	ECQB1H152K	FILM	50V	1.5nF
C3955	ECQB1H563K	FILM	50V	56nF
JSE28	ECUV1H104KBX	S.M. CAP	50V	100nF
TERMINALS AND LINKS				
JK2401	LPR1250-1150	RCA JACK		
JK2702	TJB8E013	6 PIN PUSH TERMINAL		

Cct Ref	Parts Number	Description
JK3001	0350808500	SCART SOCKET
JK3201	TJB8E026	AV TERMINAL
R2710	TSF19252	FS LINK
SWITCHES		
S802	ESB92S11B	SWITCH
S1251	EVQ21405R	SWITCH
S1252	EVQ21405R	SWITCH
S1253	EVQ21405R	SWITCH
S1254	EVQ21405R	SWITCH
S1255	EVQ21405R	SWITCH

SCHEMATIC DIAGRAMS FOR MODEL

TX-32PK2

(EURO-4 CHASSIS)


IMPORTANT SAFETY NOTICE

Components identified by  mark have special characteristics important for safety. When replacing any of these components, use only manufacturer's specified parts.

NOTE

1. RESISTOR
All resistors are carbon ¼W resistor, unless marked otherwise.
Unit of resistance is OHM (Ω) (k=1,000, M=1,000,000)
2. CAPACITORS
All capacitors are ceramic 50V unless marked otherwise.
Unit of capacitance is μ F unless otherwise stated.
3. COIL
Unit of inductance is μ H, unless otherwise stated.

4. TEST POINT



5. EARTH SYMBOL



6. VOLTAGE MEASUREMENT

Voltage is measured by a d.c. voltmeter.



Measurement conditions are as follows:

Power source a.c. 220V-240V, 50Hz

Receiving Signal Colour Bar signal (RF)

All customer controls Maximum position

- 7.



These schematic diagrams are the latest at time of printing and are subject to change without notice.

REMARKS

- a. Do not touch the hot part, or the hot and cold parts at the same time, as you are liable to a shock hazard.
- b. Do not short circuit the hot and cold circuits as electrical components may be damaged.
- c. Do not connect an instrument, such as an oscilloscope, to the hot and cold circuits simultaneously as this may cause fuse failure. Connect the earth of the instruments to the earth connection of the circuit being measured.
- d. Make sure to disconnect the power plug before removing the chassis.

NOTE

1. The Power Supply Circuit contains a circuit area, which uses a separate power supply to isolate the earth connection. The circuit is defined by HOT and COLD indications in the schematic diagram. All circuits, except the Power Circuit, are COLD.

