




11 Disassembly and Reassembly





This section of the service manual describes the disassembly and reassembly procedures for the 203B TFT-LCD monitors.




⚠ WARNING: This monitor contains electrostatically sensitive devices. Use caution when handling these components.

11-1 Disassembly

- ⚠ Cautions:**
- 1. Please the power off, before disassemble the monitor.
 - 2. Please do not use other jig except given jig when disassemble.
 - 3. Please disassemble based on given process as below.
 - 4. Back cover open JIG : BH81-00001A

Description	Picture Description
1. The monitor puts on the cushion and remove two screws on VESA cover.	 A photograph showing the back of a Samsung monitor. A black VESA cover is attached to the rear panel. Two screws securing the cover are circled in red.
	 A photograph showing the back of the monitor with the VESA cover removed, revealing the mounting holes on the rear panel.
	2. Pull up the VESA cover and remove it.  A photograph showing a hand pulling the VESA cover away from the back of the monitor.

Description	Picture Description
3. Remove 1 screws from Lamp shield	
4. Disconnect a FUNCTION Wire from PCB ASS'Y.	
5. Disconnect 4 Lamp Wire and Wire.	
6. Disconnect a LVDS Wire from Panel.	

Description	Picture Description
<p>7. Remove 4 hexa screws from PBA board which is connected PCB bracket.</p>	
<p>8. Remove 4 screws from PBA board and pull up the PBA from the bracket as picture.</p>	
<p>9. Totally disassembled PBA board.</p>	

11-2 Reassembly

Reassembly procedures are in the reverse order of disassembly procedures.

Memo