

T BESTÜCKUNGSVARIANTEN / Components

Varianti componenti CHASSIS 695 G -

Hochspannung bei 1 mA Strahlstrom! / EHT
EAT con 1 mA Iraggio!

Chassis 695	G1 0214.A2/A3	G1 0612.A2/A3
Rö 2201	A59ESF002X11	A68ESF002X11
Hochspannung	30,5 kV	30,5 kV
U D145/D157	145 V	145 V
U C16	17,5 V	17,5 V
Tr 1601	—	J108
Tr 1771	BUZ90A	BUZ91A
D 1601	—	1N5817
D 1602	—	1N5817
D 1604	3,6V/1,3W	3,6V/1,3W
D 1841	BYW76	BYW29
R 1222	—	—
R 1223	—	—
R 1404	1,2	1,2
R 1405	1,2	1,2
R 1415	100 k	100 k
R 1601	—	1,0
R 1602	—	1,0
R 1603	—	27
R 1961	1,0	1,0
C 1214	11,0 n	11,0 n
C 1217	3,3 n	3,3 n
C 1221	0,62 µ	0,68 µ
C 1225	0,62 µ	0,68 µ
C 1415	1 µ	1 µ
C 1601	—	56 n
C 1602	—	22 n
C 1709	220 µ	330 µ
C 1842	1000 µ	2200 µ
L 1224	700 µH	700 µH
L 1601	—	330 µH
T 1251	1182.1337	1182.1337
T 1601	—	Cl 15
T 1602	—	Cl 10
T 1721	FM2220	FM2220
Si 1841	F 2,5 A	F 4 A
Dr 1703	2x33 mH	2x33 mH

695 46 2030-7/5

Sicht auf gelötete Seite!
Technische Änderungen
und Irrtümer vorbehalten!

View on to soldered side!
Subject to technical changes.

Excess and emissions avoided!



